



FI-MIX6

6-Channel Professional Audio Mixer



FI-MIX6 is a compact professional 6-channel audio mixer designed for small live performances, bars, meeting rooms, home studios and mobile sound reinforcement systems.

Equipped with built-in 99 DSP multi-effects, Bluetooth streaming, USB audio interface and rich input options, it delivers flexible, reliable audio control in a portable chassis.

Product Features

- Digital display supporting U-disk MP3 playback & MP3 recording function
- Built-in Bluetooth audio for wireless music playback
- USB interface for computer audio connection & audio streaming
- AUX input interface for mobile phone audio signal access
- CH1 & CH2 support Hi-Z high-impedance input, directly compatible with electric guitars
- Each channel equipped with independent 2-band EQ (High / Low adjustment)
- Independent MUTE switch on every channel
- Dedicated FX control for DSP effect level adjustment
- Headphone monitoring output jack
- Dual 8-segment LED level meter for MAIN output signal visualization
- Balanced XLR MAIN OUT output connectors
- Compact lightweight cabinet, easy for transportation and installation

Product Applications

Small live shows, rooftop bars, cafes, conference rooms, home recording studios, event mobile sound systems, small stage performances.



Product Specification

Model	FI-MIX6
Channels	6 Input Channels
Sampling Rate & Bit Depth	32Bit / 40kHz
Effects Processor	Built-in 99 Preset DSP Digital Multi Effects
Phantom Power	+48V switchable phantom power supply for condenser microphones
Frequency Response	20Hz – 20kHz (±1dB)
Total Harmonic Distortion (THD)	<0.01% @ 1kHz, Unity Gain
Signal to Noise Ratio (SNR)	≥90dB
Channel EQ	2-band EQ (High: ±15dB @12kHz, Low: ±15dB @80Hz)
Input Impedance	Mic: 2.5kΩ / Line: 10kΩ
Max Input Level	+22dBu
Output Impedance	120Ω
Max Output Level	+28dBu
Working Voltage	AC 110V/220V 50/60Hz
Net Weight	1.45 KG
Gross Weight	2.16 KG
Net Dimension	25 × 9 × 26cm
Package Dimension	28.8 × 10.8 × 28 cm

